



BATTERY CALIBRATION

Check if the computer is updated to the last OS Version. In case update it.

Check if backlight is set on MAN or 15:

For iDive:

- a) select DISPLAY
- b) scroll to BKL LEVEL and select 10, then scroll to BKL MODE and select MAN
- c) scroll to EXIT and select, in this way you return in the main screen

For iX3M:

- a) select DISPLAY in SYSTEM SET MENU
- b) scroll to BKL LEV/MODE and select 15
- c) push A button, in this way you return to the main screen

Now start with the procedure:

- 1) Select PC MODE
- 2) Only for iDive: Push the backlight button (in this way the screen remains lighted)

This is the condition in which there is the maximum battery consumption.

- 3) Let the computer completely discharge (until it turns off)
- 4) Make a full recharge of the computer (at least 5 hours at a wall socket)

Normally at this point everything will be ok. This procedure is needed to reset the battery calibration.